

## DS Instruments - RF Switch SCPI Command List (v2.0)

Command	Example 1	Example 2	Description
RFO	RFO 1	RFO 2	Set output port
RFO?			return current port
*PING?			Identify a unit by flashing LED and sounding the buzzer
*IDN?			Return the SCPI identification string
*REV?			Return the hardware revision number
*SAVESTATE			Save the current switch path to default memory
*RST			Reset unit now
*BUZZER	*BUZZER ON	*BUZZER OFF	Mute the buzzer
*UNITNAME			Save a nickname or device tag in flash memory
*UNITNAME?			Request the device tag/nickname
*BUTTONS ON			Re-enable the manual select button
*SYSVOLTS?			Return the USB voltage level

Command terminator: LINEFEED ("\n")  
 COM Settings: 115200bps, 8bits, 1 stop, no parity, no flow control  
 \*NOTE: Leave a 5-25mS delay between sending multiple commands

|